

EAP900H

Wireless 11N Dual Band Dual Concurrent AP /WDS/Repeater

2.4GHz/5GH
900Mbps
802.11a/b/g/n

PRODUCT OVERVIEW

EAP900H equips with two powerful independent RF interfaces that support 2.4GHz 802.11b/g/n (3T3R) and 5GHz 802.11a/n (3T3R), offering bandwidth up to 450Mbps + 450Mbps to accommodate traffic-intensive applications such as multimedia streaming.

Each radio of EAP900H has been enhanced to provide higher signal strength and receive sensitivity; this will assist to reduce dead spots in your deployed WLAN and boost received signal quality on both ends of AP and wireless client devices.

EAP900H can be powered by enclosed power adapter or off-the-shelf 802.3at-compliant PoE switches; solving common power sourcing issue in the field where devices are usually placed at drop-ceiling or mounted on walls.

Each radio of EAP900H can independently operate in 3 different modes, namely Access Point, WDS AP, or WDS Bridge; this will allow multiple combinations of operation modes on single device to address deployment requirements.

Besides intuitive web-based management. EnGenius EZ Controller software utility provides user extra convenience on applying various configuration settings into devices, enabling prompt WLAN deployment and configuration update. For effective spectrum usage, EAP900H has enclosed band steering technology, enabling 5GHz-capable clients to associate with its 5GHz radio and offloading air utilization in 2.4GHz-band. In addition, EnGenius fast roaming minimizes service down-time during handoff from one base station to another.



Available at: JIA YING TRADING PTE LTD 1 Rochor Canal Road #02-67/69

1 Rochor Canal Road #02-67/69/34-37 Sim Lim Square, Singapore 188504 Tel: 63360404 Fax: 63380404 www.jiaying.com | jiaying@singnet.com.sg | email@jiaying.com

EAP900H Data sheet Version 140114

*Theoretical wireless signal rate based on IEEE standard of 802.11 a, b, g, n chipset used. Actual throughput may vary. Network conditions and

environmental factors lower actual throughput rate. ** All specifications are subject to change without notice BUSINESS CLASS





| | FEATURES |
|-------------------------|--|
| HARDWARE FEATURES | |
| Dual Radio Concurrent | One radio supports 802.11a/n, and another supports 802.11b/g/n |
| High output power | Transmit high output power programmable for different country selections |
| High Data Rate | High speed transmitting rate up to 900Mbps with 2 radios, 3T3R 802.11n |
| Multi-Function | Access point, WDS AP, WDS Bridge and Repeater |
| Long range transmitting | Transmit power control and distance control (ACK timeout) |
| SOFTWARE | |
| Multiple SSID | 8 SSID supported. Each SSID can set itself wireless or WAN access settings |
| Band Steering | Offloading 2.4Gz clients to 5GHz band so as to prevent congestion and traffic overload |
| Fast Roaming | Enable fast association when client moves from one AP to another through WPA2/PSK authentication |
| Guest Network | Allocating WiFi services to guest within the local network |
| VLAN Pass-through | Support VLAN Pass-through |
| Firmware Upgrade | Upgrading firmware via web browser, setting are reserved after upgrade |
| Reset & Backup | Reset to factory default. User can export all setting into a file via WEB |
| Ping & Trace Route | Built-in PING function & Trace Route function in Web GUI |
| Management tools | Supports Web interface (HTTP/S), SNMP v1/v2c/v3 with MIB I/II,private MIB, CLI (Telnet/SSH) |

*Theoretical wireless signal rate based on IEEE standard of 802.11 b, g, n chipset used. Actual throughput may vary. Network conditions and environmental factors lower actual throughput rate. ** All specifications are subject to change without notice





| | SPECIFICATIONS | | |
|---------------------------------|---|-----------------------|---------------------------|
| HARDWARE SPECIFICATIONS | | | |
| мси | Atheros QCA9558 | | |
| RF | Atheros QCA9558 | (2.4GHz) + QCA9580 (5 | 5GHz) |
| Memory | 256MB | | |
| Flash | 16MB | | |
| Physical Interface | 1 x 10/100/1000 BASE-T Ethernet (RJ45) with 802.3at PoE 1 x DC power connector 1 x reset button | | |
| Power Requirements | Active Ethernet (Power over Ethernet) 802.3at support Power Adapter 12V/2A | | |
| RF SPECIFICATIONS | | | |
| Available transmit power (ERIP) | 19dBm | | |
| Frequency Band | 802.11a/b/g/n | 802.11a/b/g/n | |
| Data rate | 450Mbps(2.4GHz) | 450Mbps (5GHz) | |
| | Channel | Data Rate | Rx Sensitivity (±2dBm) |
| | 802.11b (2.412 ~ | 1Mbps 2Mbps | -97 -95 |
| | 2.472GHz) | 5.5Mbps | -93 |
| | | 11Mbps | -92 |
| | | 6Mbps | -94 |
| | | 9Mbps | -94 |
| Radio Frequency Band | | 12Mbps | -90 |
| (The Max. Power may be | 802.11g (2.412 ~ | 18Mbps | -85 |
| different depending on local | 2.472GHz) | 24Mbps | -82 |
| | | 36Mbps | -80 |
| regulations) | | 48Mbps | -77 |
| | | 54Mbps | -75 |
| | | MCS0 / MCS8 | -95 |
| | 802.1n (2.412 ~ 2.472GHz | MCS1 / MCS9 | -93 |
| | | MCS2 / MCS10 | -90 |
| | | MCS3 / MCS11 | -87 |
| | | MCS4 / MCS12 | -86 / -84 |
| | | MCS5 / MCS13 | -83 / -79 |

EAP900H Data sheet Version 140114

*Theoretical wireless signal rate based on IEEE standard of 802.11 b, g, n chipset used. Actual throughput may vary. Network conditions and environmental factors lower actual throughput rate. ** All specifications are subject to change without notice





| | | MCS6 / MCS14 | -73 |
|--|---|----------------|--|
| | | MCS7 / MCS15 | -70 |
| | | MCS16/17/18/19 | -95/-93/-90/-87 |
| | | MCS 20/21 | -84 / -79 |
| | | MCS 22/23 | -73/-70 |
| | | 6Mbps | -94 |
| | | 9Mbps | -94 |
| | 802.11a (5.18 ~ 5.825GHz) | 12Mbps | -90 |
| | | 18Mbps | -85 |
| | | 24Mbps | -82 |
| | | 36Mbps | -80 |
| | | 48Mbps | -77 |
| | | 54Mbps | -75 |
| | | MCS0 / MCS8 | -95 |
| | | MCS1 / MCS9 | -93 |
| | | MCS2 / MCS10 | -90 |
| | | MCS3 / MCS11 | -87 |
| | | MCS4 / MCS12 | -86 / -84 |
| | 802.11n(5.18 ~ 5.825GHz) | MCS5 / MCS13 | -83 / -79 |
| | | MCS6 / MCS14 | -73 |
| | | MCS7 / MCS15 | -70 |
| | | MCS16/17/18/19 | -95/-93/-90/-87 |
| | | MCS 20 / 21 | -84 / -79 |
| | | MCS 22 / 23 | -73 / -70 |
| Antenna | 3 x 3dBi 2.4GHz In 3 x 5dBi 5 GHz Inte | | |
| | 2.4GHz Az | imuth-Plane | 2.4GHz Elevation-Plane |
| Antenna Radiation Patterns (Internal Antenna) | 30 30 30 30 30 30 345 0 15 30 40 40 40 5 90 105 120 125 210 195 180 165 150 150 150 150 150 150 150 15 | | 300 315 300 300 45 41 41 41 41 41 41 41 41 41 41 |

EAP900H Data sheet Version 140114

*Theoretical wireless signal rate based on IEEE standard of 802.11 b, g, n chipset used. Actual throughput may vary. Network conditions and environmental factors lower actual throughput rate. ** All specifications are subject to change without notice BUSINESS CLASS



| SOFTWARE SPECIFICATIONS Operation Mode Access Point / WDS AP/ WDS Bridge / Repeater Auto Channel Selection Setting varies by regulatory domains Supports up to 8 SSIDs per frequency band VLAN Tag / VLAN Pass-through Wireless/Network Traffic Shaping Guest Network Security Wireless/Intervention WeP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MC address filtering (up to 50 MAC) Station separation WeP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation WeE interface (HTTP/S) SNMP v1/v2c/V3 with MIB //I and private MIB CLI (Telnev/SSH) Firmware Upgrade Web interface of CLI Backup / Restore Settings Revert to factory default settings Save Configuration as default Auto Reboot Specifies interval to reboot system periodically E-mail Alert / Svislo Notification | | 5GHz Azimuth-Plane | 5GHz Azimuth-Plane | |
|--|-------------------------|---|---|--|
| Operation Mode Access Point / WDS AP/WDS Bridge / Repeater Auto Channel Selection Setting varies by regulatory domains Supports up to 8 SSIDs per frequency band VLAN Tag / VLAN Pass-through Wireless Client List Supports 802.11e/WMM Traffic Shaping Guest Network Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP 11/2C/W with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Save Configuration as Default: | | 300 285 270 255 240 225 210 20 150 20 150 20 150 20 150 20 150 20 150 20 150 20 150 150 150 150 150 150 150 15 | 300 285 270 255 240 225 210 215 210 215 210 215 210 215 210 215 210 215 210 215 215 215 215 215 215 215 215 | |
| Muto Channel Selection Setting varies by regulatory domains Supports up to 8 SSIDs per frequency band VLAN Tag / VLAN Pass-through Wireless/Network Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same VVLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB //II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Save She customized configuration as default | SOFTWARE SPECIFICATIONS | | | |
| Supports up to 8 SSIDs per frequency band VLAN Tag / VLAN Pass-through Wireless Client List Supports 802.11e/WMM Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2cv3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | Operation Mode | Access Point / WDS AP/ WDS Bridge / Re | peater | |
| Wireless/Network VLAN Tag / VLAN Pass-through Wireless Client List Supports 802.11e/WMM Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover Security WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically Specifies interval to reboot system periodically | | Auto Channel Selection Setting varies by r | egulatory domains | |
| Wireless/Network Wireless Client List Supports 802.11e/WMM Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | Supports up to 8 SSIDs per frequency bar | nd | |
| Wireless/Network Supports 802.11e/WMM Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover Security WEP encryption: 64/128/152-bit WPA/WPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | VLAN Tag / VLAN Pass-through | | |
| Wireless/Network Traffic Shaping Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CL1 (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | Wireless Client List | | |
| Guest Network - Allocates a separate network segment for guest access within the same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPA/WPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | Supports 802.11e/WMM | | |
| Management same WLAN Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | Wireless/Network | Traffic Shaping | | |
| Band Steering - Moves 5GHz-compatible clients to 5GHz band to ease traffic congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | Guest Network - Allocates a separate network segment for guest access within the | | |
| congestion on 2.4GHz band Fast Handover WEP encryption: 64/128/152-bit WPAWPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | same WLAN | | |
| Fast Handover WEP encryption: 64/128/152-bit WPA/WPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Management WEP encryption: 64/128/152-bit WPA/WPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Security WPA/WPA2 Enterprise/PSK Hidden SSID MAC address filtering (up to 50 MAC) Station separation Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically System periodically | | | | |
| Security Hidden SSID MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | WEP encryption: 64/128/152-bit | | |
| MAC address filtering (up to 50 MAC) Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Station separation Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | Security | | | |
| Web interface (HTTP/S) SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Management SNMP v1/v2c/v3 with MIB I/II and private MIB CLI (Telnet/SSH) Firmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| ManagementCLI (Telnet/SSH)Firmware UpgradeWeb interface or CLIBackup / Restore SettingsRevert to factory default settingsSave Configuration as Default:Saves the customized configuration as defaultAuto RebootSpecifies interval to reboot system periodically | | · · · · | | |
| ManagementFirmware Upgrade Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | МІВ | |
| Management Web interface or CLI Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Management Backup / Restore Settings Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Management Revert to factory default settings Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Save Configuration as Default: Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | Management | | | |
| Saves the customized configuration as default Auto Reboot Specifies interval to reboot system periodically | | | | |
| Auto Reboot Specifies interval to reboot system periodically | | | | |
| Specifies interval to reboot system periodically | | | | |
| | | | | |
| · · · · · · · · · · · · · · · · · · · | | E-mail Alert / Syslog Notification | | |

EAP900H Data sheet Version 140114

*Theoretical wireless signal rate based on IEEE standard of 802.11 b, g, n chipset used. Actual throughput may vary. Network conditions and environmental factors lower actual throughput rate. ** All specifications are subject to change without notice

BUSINESS CLASS EAP900H



| ENVIRONMENT AND MECHANICAL | | |
|----------------------------|-------------------------|--|
| Temperature Range | Operating 0℃~40℃ | |
| | Storage -20℃~60℃ | |
| Humidity (non-condensing) | 0%~90% typical | |
| Dimension | 161.5mm(D) x 41.5mm (H) | |
| Weight | 290g | |

| PACKAGE CONTENT | |
|----------------------------------|--|
| 1 x EAP900H | |
| 1 x 12V/2A Power Adapter | |
| 1 x Ethernet Cable | |
| 1 x Quick Installation Guide | |
| 1 x T-Rail Mounting kit | |
| 1 x Ceiling/Wall Mount Screw kit | |
| 1 x Mounting Bracket | |

EAP900H Data sheet Version 140114

*Theoretical wireless signal rate based on IEEE standard of 802.11 b, g, n chipset used. Actual throughput may vary. Network conditions and environmental factors lower actual throughput rate. ** All specifications are subject to change without notice BUSINESS CLASS